# MAX BR1 Pro 5G The Classic Goes Sonic



BR1 Pro 5G搭载了新一代多核心CPU,确保提供千兆级速度,比起原版BR1经典版快8倍。





Ultimate 5G Speed Blazing Fast Wi-Fi 6



# Why Settle For An Adapter When You Can Get The Full Suite?



## MAX BR1 Pro 5G





### Wi-Fi 6

体验更少的干扰并同时连接到多个设备





## **Deploy with Confidence**



就像最初的 BR1 Classic 一样, BR1 Pro 5G 也通过了认证,可以满足各种部署标准。







**EN** 61373

**EN** 50155

**EN** 6100<u>0</u>

# Low-Profile Form Factor

结构紧凑:BR1 Pro 5G只有1.15英寸, 比BR1 Classic窄25%。




1.15 inches

**5.08** inches

**5.78** inches

## MAX BR1 Pro 5G





#### **Specifications**

Wi-Fi Interface

SpeedFusion VPN

**Recommended Users** 

Cellular Data Rate 4

**AP Controller** 

WAN Interface	1x 10/100/1000/2500 Ethernet <sup>1</sup>	Antenna Connectors	4x SMA Cellular Connectors

1x Embedded Cellular Modem with 2x RP-SMA Wi-Fi Antenna Connectors Redundant SIM Slots 1x SMA GPS Antenna Connector

2x 10/100/1000M Ethernet 1 **LAN Interface Power Input** AC Adapter: AC Input 100V-240V / DC Output 12V

> Simultaneous Dual-Band (2.4GHz / 5GHz) 10V - 30V DC

Wi-Fi 6 2x2 MU-MIMO Wi-Fi WAN and/or AP **Power Consumption** 8W (nominal), 19W (max.)

SpeedFusion Features Hot Failover 2, WAN Smoothing 2, **Dimensions** 5.78 x 5.08 x 1.15 inches / 146.8 x 129 x 29.3 mm

Bandwidth Bonding<sup>2</sup> Weight 1.5 pounds / 680 grams

Number of  $2/5^{3}$ 

**Operating Temperature Peers** 

Humidity 15% – 95% (non-condensing) **Features** GPIO, Ignition Sensing

Certifications FCC, CE, RoHS,

**Router Throughput** 1Gbps E-Mark

EN61373 Shock and Vibration Resistance SpeedFusion Throughput EN50155 Railway Applications 400 Mbps

(No Encryption) Electronic Equipment used on Rolling Stock

**EN61000 Electromagnetic Compatibility** 

SpeedFusion Throughput 200 Mbps

(256-bit AES) **Package Content** 4x LTE/5G Antennas (ACW-235)

> 1-150 2x Dual Band Wi-Fi Antennas (ACW-341)

1x GPS Active Antenna (ACW-232) 1x 12V 2A 4 Pin Power Supply (ACW-632)

-40° - 149°F / -40° - 65°C

1x BR1 Pro 5G

**Maximum Number of** 30 **SIM Card Size** Nano-SIM (4FF)

**AP Supported** Warranty 1-Year Limited Warranty

(Downlink / Uplink) CAT-20: 2 Gbps / 150 Mbps

5G: 4 Gbps / 700 Mbps

Standard

Specifications are subject to change without notice.

Ethernet ports include surge and ESD protection circuits to protect against over-voltage transients.

Requires a PrimeCare subscription, complimentary for the first year.
S SpeedFusion VPN Peers are enabled for PrimeCare models which requires a PrimeCare subscription, complimentary for the first year.

<sup>&</sup>lt;sup>4</sup> Maximum theoretical data rates.

## MAX BR1 Pro 5G



#### **Ordering Information**

**Product Code** 

MAX-BR1-PRO-5GD-T-PRM Embedded Modem(s):

1x 5G

Regions

Primary: APAC, EMEA Compatibility: Global **5G Bands** 

n1, n2, n3, n5, n7, n8, n12, n20, n28, n38, n41, n66, n71, n77, n78,

n79

**LTE Bands** 

B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39,

B40, B41, B42, B46, B66, B71

MAX-BR1-PRO-5GH-T-PRM

Embedded Modem(s): 1x 5G

Primary: North America\* Compatibility: Global

US Carrier Certifications: AT&T, T-Mobile, US Cellular, Verizon (C-Band), FirstNet 5G (NSA) Sub 6Ghz:

5G (NSA) Sub 6Ghz:

n1, n2, n3, n5, n28, n41, n66, n71, n77, n78, n79

B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71

#### **Featured Add-ons**

Product Code Description

PRM-C-1Y / PCP-C-1Y PrimeCare C / PrimeCare+ C (1-Year)

PRM-C-2Y / PCP-C-2Y PrimeCare C / PrimeCare+ C (2-Year)

PRM-C-4Y / PCP-C-4Y PrimeCare C / PrimeCare+ C (4-Year)

ACW-634 10ft DC Power Cable

ACW-643 Vehicle Cigarette to Molex Power Cable

ANT-MB-42G-S-B-6 7-in-1 Cellular and Wi-Fi Antenna System with GPS Receiver (Black)

ANT-MB-42G-S-W-6 7-in-1 Cellular and Wi-Fi Antenna System with GPS Receiver (White)